



Base/Bracket Mounting



Tube mounting



Accessories

**i TECHNICAL SPECIFICATIONS/ORDER SPECIFICATIONS:**

	Base/Bracket mounting	Tube mounting
Dimensions (Ø x Height):	98 mm x 137 mm	98 mm x 200 mm
Cable entry:		Cable diameter 5-7 mm
Housing:		PC/ABS-Blend
Lens:		PC, transparent

**FLASHING BEACON 828**

Connection:	Screw terminal 0.5 - 1.5 mm <sup>2</sup>
Flash energy:	5 Ws
Flash frequency:	C. 1 Hz
Life duration:	4 x 10 <sup>6</sup> flashes

12 V: Safety contact is triggered by removal of lens.

**Base/Bracket mounting**

	12 V DC	24 V DC	10-60 V AC/DC	115 V AC	230 V AC
Current consumption:	500 mA	300 mA	500-120 mA	65 mA	150 mA
red	<b>828 100 54</b>	<b>828 100 55</b>	<b>828 180 70</b>	<b>828 100 67</b>	<b>828 100 68</b>
yellow	<b>828 300 54</b>	<b>828 300 55</b>	<b>828 380 70</b>	<b>828 300 67</b>	<b>828 300 68</b>
clear	-	<b>828 400 55</b>	<b>828 480 70</b>	-	<b>828 400 68</b>

**Tube mounting**

	24 V DC	115 V DC	230 V AC
red	<b>828 140 55</b>	<b>828 140 67</b>	<b>828 140 68</b>
yellow	<b>828 340 55</b>	<b>828 340 67</b>	<b>828 340 68</b>
clear	<b>828 440 55</b>	-	-

**FLASHING BEACON 828 WITH 2 FREQUENCIES**

Connection:	Screw terminal 0.5 - 1.5 mm <sup>2</sup>
Flash energy:	5 Ws
Flash frequency:	0.5 Hz or 1.5 Hz can be set externally
Life duration:	4 x 10 <sup>6</sup> flashes

	Base/Bracket mounting	Tube mounting
Voltage:	24 V DC	24 V DC
Current consumption:	500 mA	500 mA
red	<b>828 120 55</b>	<b>828 160 55</b>
yellow	<b>828 320 55</b>	<b>828 360 55</b>

**ACCESSORIES:**

Accessories see page 146.



**TECHNICAL DIAGRAM:**



828 X00 XX  
828 X40 XX  
828 X20 XX  
828 X60 XX

Base/Bracket mounting

Tube mounting



**Signalisation index**

Xenon Flashing Light

